

FEATURES

- ✓ Low current consumption
- ✓ Three terminal design with resistive and non-resistive terminals
- ✓ Suits System Sensor and other brands
- ✓ Compatible with conventional or addressable detectors
- ✓ Easy to install
- ✓ Pre drilled counter sunk holes



PRODUCT DESCRIPTION

Our slim line remote indicators are unobtrusive and easy to install. A full range of remote indicators are available to compliment the fire alarm systems offered by FireSense.

The following types are available:

- ✓ In Concealed Space
- ✓ In Roof
- ✓ In Room

TECHNICAL SPECIFICATIONS

Current	15mA max.
Brightness	9mcd
Voltage	15Vdc to 24Vdc
Terminals	(Common D -) (Resistive R+) (Non resistive D+)

CONNECTIONS

Type	Detector Base	Remote indicator
System Sensor Conventional Base B401	Terminals 1+ and 2 -	D - and R+
System Sensor Conventional Base B401R	Terminals 1+ and 2 -	D - and D+
System Sensor Addressable Base B501	Terminals 3+ and 1 -	D - and R+
Hochiki Conventional Base YB0-R/4A	Terminals 3+ and 6 -	D - and D+

ORDERING INFORMATION

Product Code	Description
RIP-FA-CON	Remote indicator - (FIRE ALARM - IN CONCEALED SPACE)
RIP-FA-ROOF	Remote indicator -(FIRE ALARM - IN ROOF)
RIP-FA-ROOM	Remote indicator - (FIRE ALARM - IN ROOM)