

#### FEATURES

- ✓ Wide input voltage range
- ✓ Up to 100mA output
- ✓ Suitable for external use
- ✓ Compatible with our FLASHNI, ROSHNI, STR-FULL and Solista strobe range



#### PRODUCT DESCRIPTION

The FULL-MAINS-BASE has a built-in miniature 24V supply that allows any of our ROSHNI, FLASHNI, STR-FULL or Solista strobe range to function straight off 240VAC. This is suitable for many applications, such as excessive runs of cable to reach the strobes or sounders.

#### TECHNICAL SPECIFICATIONS

Input Voltage	110-230VAC @ 50-60Hz
Output Voltage	24Vdc
Output Current	100mA max
Temperature	-10°C to +55°C
IP Rating	IP65
Construction	FR ABS (Deep Base)
Weight	0.1kg
Colour	Red or White

#### ORDERING INFORMATION

FULL-MAINS-BASE	Red 240V mains deep base
FULL-MAINS-BASE-W*	White 240V mains deep base

\*Indent item, lead times may apply.

#### DIMENSIONS

